

# EL-Skyport SPEED

## EL-Skyport Single Modules

---

EL-Skyport Transmitter Speed // 19350

EL-Skyport Universal Receiver Speed // 19347

EL-Skyport Universal Receiver Speed REPLACE // 19346

EL-Skyport USB RX Speed // 19348

EL-Skyport Transceiver RX // 19353

EL-Skyport Transmitter ECO // 19349

EL-Skyport Sync Adapter 3.5 – PC (female) // 11126

## EL-Skyport Sets

---

EL-Skyport Universal Speed Set // 19357

EL-Skyport RX Trigger Set // 19358

EL-Skyport RX Trigger / Computer Remote Speed Set // 19359

## EL-Skyport Transmitter Speed

- New housing design with improved touch and function buttons
- New Hot shoe with locking ring and improved contacts for best possible connectivity
- Speed Sync Feature, enables fast synchronization with SLR cameras up to 1/250 s
- New battery drawer ensures reliable contact with the battery
- All over increased distance range by 20% in Normal Sync mode.
- Status LED: Flashes once every 5 s in Normal Sync mode
- Status LED: Flashes twice every 5 s in Speed Sync mode
- Status LED indicates the Charging mode
- The LED indicates the Battery Status. At low LED brightness, exchange the battery
- The Speed Sync mode will reduce the distance range by about 40%



## EL-Skyport Universal Receiver Speed

- New housing design with improved touch and function buttons
- Improved compatibility to non Elinchrom Camera On Speed Flashes
- Camera Remote Function, the Universal can shoot remotely Nikon / Canon cameras. This feature requires special Camera Remote cables.
- **Speed Sync** function to sync cameras up to 1/250 s
- Increased distance range by 20% in Normal Sync mode.
- Status LED: Flashes once every 5 s in **Normal Sync** mode
- Status LED: Flashes twice every 5 s in **Speed Sync** mode
- Status LED indicates the **Charging** mode
- The LED indicates the **Battery** status
- Can be used with external **Battery Backup Pack's** for charging and operating the Universal Speed up to 60 hours.
- New PC- 3.5 mm Sync Adapter
- Reduced distance range by 40 – 50% when used with the Speed Sync mode



## EL-Skyport USB RX Speed

- Improved compatibility with the latest MAC™ and Win™ USB hardware



## EL-Skyport Transmitter ECO

- **Speed Sync** Feature, enables fast synchronization with SLR cameras up to 1/250 s
- Super lightweight and small
- Battery life up to 30000 flashes
- Distance range is around **50 m in Normal Sync** and **30 m in Speed Sync** mode
- Four **Frequency Channels**, no Group settings
- Status LED flashes once or twice depending if Normal-or Speed Sync mode is selected
- The LED indicates the Battery Status. At low LED brightness, exchange the battery

